

TYPE: 94-Character Graphic Character Set	REGISTRATION NUMBER: 150 DATE OF REGISTRATION: 1st Nov.1988
ESCAPE SEQUENCE:	G0: ESC 2/8 2/1 4/0 G1: ESC 2/9 2/1 4/0 G2: ESC 2/10 2/1 4/0 G3: ESC 2/11 2/1 4/0 C0: - C1: -
NAME Greek Primary Set of Graphic Characters	
DESCRIPTION <p>This is a 94 graphic character set to be used in either a 7-bit or an 8-bit environment.</p> <p>The names of the characters in this registration correspond to the terminology of the Registration Authority. They do not always correspond to the names used in the CCITT documents.</p>	
SPONSOR CCITT Comité Consultatif International Télégraphique et Téléphonique Place des Nations CH-1211 GENEVA 20 / Switzerland	
ORIGIN CCITT Administrations and Recognized Private Operating Agencies	
FIELD OF UTILISATION Videotex and other telematic applications. <p>This registration corresponds to work of CCITT. If required at a later stage, this registration may be amended under the procedure of clause 8.2 of ISO 2375. In this case the already allocated escape sequence will remain unchanged.</p> <p style="text-align: center;">3.484</p>	

					b ₇	0	0	0	0	1	1	1	1	
					b ₆	0	0	1	1	0	0	1	1	
					b ₅	0	1	0	1	0	1	0	1	
						0	1	2	3	4	5	6	7	
b ₄	b ₃	b ₂	b ₁						0	α	Π	⊗	π	
0	0	0	0	0					!	1	Α	Ρ	α	ρ
0	0	1	0	2					"	2	Β	⊗	β	ς
0	0	1	1	3					#	3	Γ	Σ	γ	σ
0	1	0	0	4					α	4	Δ	Τ	δ	τ
0	1	0	1	5					%	5	Ε	Υ	ε	υ
0	1	1	0	6					&	6	Ζ	Φ	ζ	φ
0	1	1	1	7					'	7	Η	Χ	η	χ
1	0	0	0	8					(8	Θ	Ψ	θ	ψ
1	0	0	1	9)	9	Ι	Ω	ι	ω
1	0	1	0	10					*	:	Κ	⊗	κ	⊗
1	0	1	1	11					+	;	Λ	[λ	{
1	1	0	0	12					,	<	Μ	\	μ	
1	1	0	1	13					-	=	Ν]	ν	}
1	1	1	0	14					.	>	Ξ	^	ξ	~
1	1	1	1	15					/	?	Ο	_	ο	⊗

Pos.	Name	Note
2/1	EXCLAMATION MARK	
2/2	QUOTATION MARK	
2/3	NUMBER SIGN	
2/4	CURRENCY SIGN	
2/5	PERCENT SIGN	
2/6	AMPERSAND	
2/7	APOSTROPHE	
2/8	LEFT PARENTHESIS	
2/9	RIGHT PARENTHESIS	
2/10	ASTERISK	
2/11	PLUS SIGN	
2/12	COMMA	
2/13	LONG HORIZONTAL BAR	1
2/14	FULL STOP	
2/15	SOLIDUS	
3/0	DIGIT ZERO	
3/1	DIGIT ONE	
3/2	DIGIT TWO	
3/3	DIGIT THREE	
3/4	DIGIT FOUR	
3/5	DIGIT FIVE	
3/6	DIGIT SIX	
3/7	DIGIT SEVEN	
3/8	DIGIT EIGHTH	
3/9	DIGIT NINE	
3/10	COLON	
3/11	SEMICOLON (Greek question mark)	
3/12	LESS-THAN SIGN	
3/13	EQUALS SIGN	
3/14	GREATER-THAN SIGN	
3/15	QUESTION MARK	

Pos.	Name	Note
4/0	COMMERCIAL AT	
4/1	CAPITAL GREEK LETTER ALPHA	
4/2	CAPITAL GREEK LETTER BETA	
4/3	CAPITAL GREEK LETTER GAMMA	
4/4	CAPITAL GREEK LETTER DELTA	
4/5	CAPITAL GREEK LETTER EPSILON	
4/6	CAPITAL GREEK LETTER ZETA	
4/7	CAPITAL GREEK LETTER ETA	
4/8	CAPITAL GREEK LETTER THETA	
4/9	CAPITAL GREEK LETTER IOTA	
4/10	CAPITAL GREEK LETTER KAPPA	
4/11	CAPITAL GREEK LETTER LAMBDA	
4/12	CAPITAL GREEK LETTER MU	
4/13	CAPITAL GREEK LETTER NU	
4/14	CAPITAL GREEK LETTER XI	
4/15	CAPITAL GREEK LETTER OMICRON	
5/0	CAPITAL GREEK LETTER PI	
5/1	CAPITAL GREEK LETTER RHO	
5/2	This position shall not be used	2
5/3	CAPITAL GREEK LETTER SIGMA	
5/4	CAPITAL GREEK LETTER TAU	
5/5	CAPITAL GREEK LETTER UPSILON	
5/6	CAPITAL GREEK LETTER PHI	
5/7	CAPITAL GREEK LETTER CHI	
5/8	CAPITAL GREEK LETTER PSI	
5/9	CAPITAL GREEK LETTER OMEGA	
5/10	This position shall not be used	
5/11	LEFT SQUARE BRACKET	
5/12	REVERSE SOLIDUS	
5/13	RIGHT SQUARE BRACKET	
5/14	CIRCUMFLEX ACCENT	
5/15	LOW LINE	

Pos.	Name	Note
6/0	This position shall not be used	
6/1	SMALL GREEK LETTER ALPHA	
6/2	SMALL GREEK LETTER BETA	
6/3	SMALL GREEK LETTER GAMMA	
6/4	SMALL GREEK LETTER DELTA	
6/5	SMALL GREEK LETTER EPSILON	
6/6	SMALL GREEK LETTER ZETA	
6/7	SMALL GREEK LETTER ETA	
6/8	SMALL GREEK LETTER THETA	
6/9	SMALL GREEK LETTER IOTA	
6/10	SMALL GREEK LETTER KAPPA	
6/11	SMALL GREEK LETTER LAMBDA	
6/12	SMALL GREEK LETTER MU	
6/13	SMALL GREEK LETTER NU	
6/14	SMALL GREEK LETTER XI	
6/15	SMALL GREEK LETTER OMICRON	
7/0	SMALL GREEK LETTER PI	
7/1	SMALL GREEK LETTER RHO	
7/2	SMALL GREEK LETTER FINAL SIGMA	
7/3	SMALL GREEK LETTER SIGMA	
7/4	SMALL GREEK LETTER TAU	
7/5	SMALL GREEK LETTER UPSILON	
7/6	SMALL GREEK LETTER PHI	
7/7	SMALL GREEK LETTER CHI	
7/8	SMALL GREEK LETTER PSI	
7/9	SMALL GREEK LETTER OMEGA	
7/10	This position shall not be used	
7/11	LEFT CURLY BRACKET	
7/12	VERTICAL LINE	1
7/13	RIGHT CURLY BRACKET	
7/14	MACRON	

NOTES

- 1 The graphic symbol representing this character shall be designed so as to occupy the full length or height, respectively, of the character box so as to be jointive.
- 2 Telematic terminals should not transmit this bit combination. However, to ensure compatibility with some conversion equipments, when a telematic terminal receives bit combination 5/2, it shall interpret it as CAPITAL GREEK LETTER SIGMA.